

The following page (in construction) describes the simulation of devices with open boundary conditions such as RTDs with the nextnano.NEGF software.

Note that in the current version (2020-11-19), only single band calculations are supported for open boundary conditions.

Simulation of devices with open boundary conditions

In order to simulate a system with open boundary conditions (instead of the default field-periodic boundary condition), contacts have to be defined by adding a <Contacts> section in the input file:

```
<Contacts>
  <DensityLeft unit="cm^-3">1e18</DensityLeft>
  <DensityRight unit="cm^-3">1e18</DensityRight>
  <MaterialLeft>well</MaterialLeft>
  <MaterialRight>well</MaterialRight>

  <Broadening unit="meV">10.0</Broadening>
  <Ballistic>no</Ballistic>
</Contacts>
```

In this section, the carrier densities in the left and right contact have to be defined using the <DensityLeft> and <DensityRight> commands, as shown above. The unit is cm^{-3} .

The material of the left and right contacts needs to be defined by the command <MaterialLeft> and <MaterialRight>. The string value has to be an alias defined in the <Materials> section of the input file.

A broadening energy can be defined by the command <Broadening>. Indeed, scattering is not accounted in the contact, so that this command allows a phenomenological broadening of the density of states in the contact.

The command <Ballistic> can be used to calculate ballistic transport between the contacts (i.e. no scattering process considered) if its value is set to yes.

The tutorial for AlGaAs/GaAs intraband RTD is available on our new manual from [here](#).

From:
<https://nextnano-docu.northeurope.cloudapp.azure.com/dokuwiki/> - nextnano.NEGF - Software for Quantum Transport

Permanent link:
https://nextnano-docu.northeurope.cloudapp.azure.com/dokuwiki/doku.php?id=qcl:simulation_of_resonant_tunneling_diodes_rtds&rev=1645103283

Last update: 2022/02/17 13:08